




Figure can vary

0 ... 2m

- Miniature throughbeam photoelectric sensor with visible red light
- Homogeneous, highly visible light spot by means of pin-point LED
- Universal connection options
- Miniature construction with temperature-stable plastic housing with protection class IP 67 and 2 inlaid metal fastening sleeves for secure mounting
- Activation input (option)

### Dimensioned drawings



**A** Transmitter  
**B** Yellow indicator diode  
**C** Green indicator diode

All dimensions in millimeters

### Accessories:

(available separately)

- Mounting device BT 002 M.5 (50112206)
- Cable with M8 or M12 connector (K-D ...)

### Electrical connection

## Transmitter

Plug connection, 4-pin	10–30V DC +	1 br/BN	10–30V DC +	1 br/BN
	NC 2	bl/BU	OUT 2	ws/WH
Plug connection, 3-pin	GND 3		GND	bl/BU
	NC 4		OUT 1	sw/BK
Cable, 4 wires	10–30V DC +	1 br/BN	10–30V DC +	1 br/BN
	GND	bl/BU	GND	bl/BU
	activ	sw/BK	OUT 1	sw/BK
	NC		OUT 2	ws/WH
	GND		bl/BU	
	NC		sw/BK	

## Receiver

## Technical data

### Optical data

Typ. operating range limit 1)	0 ... 2m
Operating range 2)	0 ... 1.6m
Light source 3)	LED (modulated light)
Wavelength	640nm (visible red light)

### Timing

Switching frequency	385Hz
Response time	1.3ms
Repeatability	175µs
Delay before start-up	≤ 120ms

### Electrical data

Operating voltage $U_B$ 4)	10 ... 30VDC (incl. residual ripple)
Residual ripple	≤ 10% of $U_B$
Open-circuit current	≤ 20mA
Switching output	.../42 OUT1 (pin 4): PNP light switching OUT2 (pin 2): NPN light switching .../42D OUT1 (Pin 4): PNP dark switching OUT2 (Pin 2): NPN dark switching .../4 OUT1 (pin 4): PNP light switching bipolar transistor with open collector, leakage current (OFF): PNP=10µA, NPN=10µA, saturation voltage (ON, at 50mA): PNP=2V, NPN=2V max. 50mA (per output and total) $C \leq 2.2\mu F$
Output configuration	
Output current	
Load	

### Indicators

Green LED in continuous light	ready
Green LED, flashing	output overloaded
Yellow LED in continuous light	light path free
Yellow LED, flashing	light path free, no performance reserve

### Mechanical data

Housing	plastic (TPE)
Optics cover	plastic (PC)
Attachment	by means of 2 brass sleeves integrated in the housing
Weight	with 2m cable: 50g with 150mm cable and connector: 20g
Connection type	2m cable, PVC, 4-wire, core cross section 4x0.14mm <sup>2</sup> , 150mm cable with M8/M12 connector, 4-pin

### Environmental data

Ambient temp. (operation/storage)	-20°C ... +55°C/-30°C ... +75°C
Protective circuit 5)	1, 2, 3, 4
VDE safety class	III
Protection class	IP 67
LED class	1 (acc. to EN 60825-1)
Standards applied	IEC 60947-5-2
Certifications	cURus (Recognized Component Mark for Canada and USA)

### Options

Activation input activ (only LSSR 2.8, 150-S8.3)	-
Transmitter active/not active	$\geq 8V \leq 2V$
Activation/disable delay	$\leq 1ms$

1) Typ. operating range limit: max. attainable range without performance reserve

2) Operating range: recommended range with performance reserve

3) Average life expectancy 100,000h at an ambient temperature of 25°C

4) For UL applications: for use in class 2 circuits according to NEC only

5) 1=overload protection, 2=polarity reversal protection, 3=short circuit protection for all transistor outputs,  
4=transient protection max.  $\pm 50V$


## Tables

0	1.6	2
---	-----	---

Operating range [m]  
 Typ. scanning range limit [m]

## Diagrams

Typ. response behavior



## NOTES



### Operate in accordance with intended use!

↳ This product is not a safety sensor and is not intended as personnel protection.

↳ The product may only be put into operation by competent persons.

↳ Only use the product in accordance with the intended use.

A light axis consists of a transmitter and a receiver with the following designations:

LSR = Complete light axis

LSSR = Transmitter

LSER = Receiver

## Part number code

**LSSR 2 / 42 D , 150 - S12**

## Operating principle

Operating principle	
<b>HRTR</b>	Miniature light scanners with background suppression, red light
<b>PRK</b>	Miniature retro-reflective photoelectric sensor with polarization filter
<b>LSSR</b>	Miniature throughbeam photoelectric sensor, red-light transmitter
<b>LSER</b>	Miniature throughbeam photoelectric sensor, red-light receiver

## Series

**2** 2 Series  
**2.8** With activation input

## Switching output

Switching output	
I42	Bipolar transistor output open collector, OUT 1 (pin 4): PNP, OUT 2 (pin 2): NPN
I4	Bipolar transistor output open collector, OUT 1 (pin 4): PNP, OUT 2 (pin 2): does not exist

## Switching output function

N/A OUT 1 and OUT 2 both light switching  
D OUT 1 and OUT 2 both dark switching

#### Scanning range (only with operating principle HRTR)

- 15F Scanning range limit set to 15mm
- 30F Scanning range limit set to 30mm
- 50F Scanning range limit set to 50mm

## Electrical connection

<b>N/A</b>	Cable, PVC, standard length 2000mm, 4-wire
<b>.150-S8</b>	Cable, PVC, length 150mm with M8 connector, 4-pin, axial
<b>.150-S8.3</b>	Cable, PVC, length 150mm with M8 connector, 3-pin, axial
<b>.150-S12</b>	Cable, PVC, length 150mm with M12 connector, 4-pin, axial

## Order guide

The sensors listed here are preferred types; current information at [www.leuze.com](http://www.leuze.com)

### Order code

**Part No.**

## Transmitter

LSSR 2	50112127
LSSR 2, 150-S8	50112128
LSSR 2.8, 150-S8.3	50116172
LSSR 2, 150-S12	50112129

receiver

LSER 2/42	50112130
LSER 2/42, 150-S8	50112131
LSER 2/4, 150-S8.3	50116173
LSER 2/42, 150-S12	50112132
LSER 2/42D	50112133
LSER 2/42D, 150-S8	50112134
LSER 2/42D, 150-S12	50112135