



Basic features

| | |
|---|---|
| Application | Object detection |
| Approval/Conformity | CE UKCA cULus Ecolab WEEE |
| Basic standard | IEC 60947-5-2 |
| Operating mode | SIO Mode IO-Link Mode |
| Scope of delivery | 2x nut M18x1 |
| Secondary features for condition monitoring | Vibration monitoring Inclination monitoring and installation aid Internal temperature monitoring Internal humidity detection |

Display/Operation

| | |
|--------------------|-----|
| Function indicator | yes |
| Power indicator | no |

Electrical connection

| | |
|-----------------------------------|----------------------------|
| Connection | M12x1-Male, 4-pin, A-coded |
| Polarity reversal protected | yes |
| Protection against device mix-ups | yes |
| Short-circuit protection | yes |

Electrical data

| | |
|-----------------------------------|--------------|
| Load capacitance max. at Ue | 0.25 μ F |
| Min. operating current Im | 0 mA |
| No-load current Io max., damped | 18 mA |
| No-load current Io max., undamped | 18 mA |
| Operating voltage Ub | 10...30 VDC |
| Output resistance Ra | 100.0 kOhm |
| Rated operating current Ie | 100 mA |
| Rated operating voltage Ue DC | 24 V |
| Rated short circuit current | 100 A |
| Ready delay tv max. | 300 ms |
| Ripple max. (% of Ue) | 15 % |
| Switching frequency | 700 Hz |
| Utilization category | DC -13 |
| Voltage drop static max. | 1.5 V |

Environmental conditions

| | |
|-------------------------|---------------------------------|
| Ambient temperature | -40...85 °C |
| Contamination scale | 3 |
| EN 60068-2-27, Shock | Half-sinus, 30 gn, 11 ms |
| EN 60068-2-6, Vibration | 55 Hz, amplitude 1 mm, 3x30 min |
| IP rating | IP68, IP69K |

Functional safety

| | |
|--------------|---------|
| MTTF (40 °C) | 443.6 a |
|--------------|---------|

Smart Automation and Monitoring System
Inductive Sensors
BES M18EH1-L01C80B-S04G-L04
Order Code: BES05WY

BALLUFF

IO-Link

| | |
|----------------------------|-------------------------------------|
| IO-Link Profil IDs | 0x0004 SSP2.1 |
| | 0x0005 SSP2.2 |
| | 0x0006 SSP2.3 |
| | 0x4000 Identification and Diagnosis |
| Supported IO-Link Profiles | Common Profile |
| | Legacy Smart Sensor Profile |
| | Smart Sensor Profile - Adjustable |
| | Switching Sensor |

Interface

| | |
|--------------------------|-----------------------------|
| Interface | IO-Link 1.1 |
| Interface setting option | Factory setting (Reset) |
| | SIO mode/IO-Link mode |
| | Teach-In of switchpoints |
| Process data IN | Teaching successfully reply |
| | 1 byte |
| | Switching state |
| Switching output | PNP/NPN/push-pull NO/NC |
| | Push-pull NO/NC |

Material

| | |
|--------------------------|------------------------|
| Housing material | 1.4404 stainless steel |
| Material sensing surface | PBT |

Mechanical data

| | |
|-------------------|--------------|
| Dimension | Ø 18 x 66 mm |
| Installation | quasi-flush |
| Mounting length | 45 mm |
| Size | M18x1 |
| Tightening torque | 15 Nm |

Range/Distance

| | |
|----------------------------------|------------|
| Assured operating distance Sa | 6.4 mm |
| Hysteresis H max. (% of Sr) | 15.0 % |
| Measuring range | 0.5...8 mm |
| Rated operating distance Sn | 8 mm |
| Repeat accuracy max. (% of Sr) | 5.0 % |
| Switching distance marking | ■ ■ |
| Temperature drift max. (% of Sr) | 10 % |
| Tolerance Sr | 10 % |

Remarks

After eliminating the overload, the sensor must be disconnected from the supply voltage. The sensor is then functional again.

Sensors with IO-Link function are not suitable for series or parallel wiring.

Find the installation instructions for inductive sensors in the download area of the sensor on the homepage.

For more information about MTTF and B10d see MTTF / B10d Certificate

Indication of the MTTF- / B10d value does not represent a binding composition and/or life expectancy assurance; these are simply experiential values with no warranty implications. These declared values also do not extend the expiration period for defect claims or affect it in any way.

Connector Drawings



Wiring Diagrams

