




Operating Manual

mic+ Ultrasonic Sensors with two switching outputs

mic+25/DD/TC
mic+35/DD/TC
mic+130/DD/TC
mic+340/DD/TC
mic+600/DD/TC

mic+25/EE/TC
mic+35/EE/TC
mic+130/EE/TC
mic+340/EE/TC
mic+600/EE/TC

Diagram 1: Set sensor parameters numerically using LED display



settings can be adjusted by a Windows® Software.

Safety Notes

- The mic+ sensor with two switching outputs measures the distance to an object within the detection zone contactless. Depending on the adjusted detect distance the switching output is set.
- All settings are done with two push-buttons and a three-digit LED-display (TouchControl).
- Three-colour LEDs indicate the switching status.
- The output functions are changeable from NOC to NCC.
- The sensors are adjustable manually via TouchControl or via Teach-in procedure.
- Useful additional functions are set in the Add-on-menu.
- Using the LinkControl adapter (optional accessory) all TouchControl and additional sensor parameter

Proper Use

mic+ ultrasonic sensors are used for non-contact detection of objects.

The mic+ sensors have a **blind zone** in which distance measurement is not possible. The **operating range** indicates the distance of the sensor that

can be applied with normal reflectors with sufficient function reserve. When using good reflectors, such as a calm water surface, the sensor can also be used up to its **maximum range**. Objects that strongly absorb (e.g. plastic foam) or diffusely reflect sound (e.g. pebble stones) can also reduce the defined operating range.

Synchronisation

If the assembly distances shown in Fig. 1 for two or more sensors are exceeded the integrated synchronisation should be used. Connect Sync/Com-channels (pin 5 at the units receivable) of all sensors (10 maximum).

	↓	↔
mic+25...	≥0.35 m	≥2.50 m
mic+35...	≥0.40 m	≥2.50 m
mic+130...	≥1.10 m	≥8.00 m
mic+340...	≥2.00 m	≥18.00 m
mic+600...	≥4.00 m	≥30.00 m

Fig. 1: Assembly distances, indicating synchronisation/multiplex

Multiplex mode

The Add-on-menu allows to assign an individual address »01« to »10« to each sensor connected via the Sync/Com-channel (Pin5). The sensors perform the ultrasonic measurement sequentially from low to high address. Therefore any influence between the sensors is rejected.

The address »00« is reserved to synchronisation mode and deactivates the multiplex mode. To use synchronised mode all sensors must be set to address »00«.

Installation

- ➔ Assemble the sensor at the installation location.
- ➔ Plug in the connector cable to the M12 connector, see Fig. 2.




Fig. 2: Pin assignment with view onto sensor plug and colour coding of the microsonic connection cable

Start-up

- ➔ Connect the power supply.
- ➔ Set the parameters of the sensor manually via TouchControl (see Fig. 3 and Diagram 1)
- ➔ or use the Teach-in procedure to adjust the detect points (see Diagram 2).




Fig. 3: TouchControl/LED display

Factory setting

mic+ sensors are delivered factory made with the following settings:

- Switching outputs on NOC
- Detecting distance at operating range and half operating range
- Measurement range set to maximum range

Maintenance

mic+ sensors work maintenance free. Small amounts of dirt on the surface do not influence function. Thick layers of dirt and caked-on dirt affect sensor function and therefore must be removed.

Notes

- mic+ sensors have internal temperature compensation. Because the sensors heat up on their own, the temperature compensation reaches its optimum working point after approx. 30 minutes of operation.
- During normal operating mode, a yellow LED signals that the switching output has connected.
- During normal operating mode, the measured distance value is displayed on the LED-indicator in mm (up to 999 mm) or cm (from 100 cm). Scale switches automatically and is indicated by a point on top of the digits.
- During Teach-in mode, the hysteresis loops are set back to factory settings.
- If no objects are placed within the detection zone the LED-indicator shows »---«.
- If no push-buttons are pressed for 20 seconds during parameter setting mode the made changes are stored and the sensor returns to normal operating mode.

Diagram 2: Set sensor parameters via Teach-in procedure




Diagram 3: Key lock and factory setting








Diagram 4: Useful additional functions in Add-on menu (for experienced users only, settings not required for standard applications)




Technical data




mic+25...




mic+35...




mic+130...



mic+340...








mic+600...



blind zone: 0 to 30 mm
operating range: 250 mm
maximum range: 350 mm
angle of beam spread: see detection zone
transducer frequency: 320 kHz
resolution: 0.025 mm

detection zones

for different objects:
 The dark grey areas represent the zone where it is easy to recognise the normal reflector (round bar). This indicates the typical operating range of the sensors. The light grey areas represent the zone where a very large reflector – for instance a plate – can still be recognised. The requirement here is for an optimum alignment to the sensor. It is not possible to evaluate ultrasonic reflections outside this area.



reproducibility/accuracy

±0.15 %
±1 % (Temperature drift internal compensated, may be deactivated³⁾, 0.17%/K without compensation)operating voltage U_B: 9 to 30 V DC, short-circuit-proof, Class 2

voltage ripple: ±10 %

no-load supply current: ≤ 80 mA

housing: Brass sleeve, nickel-plated, plastic parts: PBT, TPU; Ultrasonic transducer: polyurethane foam, epoxy resin with glass content

class of protection to EN 60529: IP 67

norm conformity: EN 60947-5-2

type of connection: 5-pin initiator plug, PBT

controls: 2 push-buttons (TouchControl)

indicators: 3-digit LED display, 2 three-colour LEDs with TouchControl and LinkControl

programmable: programmable

operating temperature: -25 to +70 °C

storage temperature: -40 to +85 °C

weight: 150 g

switching hysteresis¹⁾: 3 mmswitching frequency²⁾: 25 Hzresponse time²⁾: 32 ms

time delay before availability: <300 ms

order No. mic+25/DD/TC

switching output: 2 x pnp, U_B - 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

order No. mic+25/EE/TC

switching output: 2 x npn, -U_B + 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+35...

±0.15 %
±1 % (Temperature drift internal compensated, may be deactivated³⁾, 0.17%/K without compensation)operating voltage U_B: 9 to 30 V DC, short-circuit-proof, Class 2

voltage ripple: ±10 %

no-load supply current: ≤ 80 mA

housing: Brass sleeve, nickel-plated, plastic parts: PBT, TPU; Ultrasonic transducer: polyurethane foam, epoxy resin with glass content

class of protection to EN 60529: IP 67

norm conformity: EN 60947-5-2

type of connection: 5-pin initiator plug, PBT

controls: 2 push-buttons (TouchControl)

indicators: 3-digit LED display, 2 three-colour LEDs with TouchControl and LinkControl

programmable: programmable

operating temperature: -25 to +70 °C

storage temperature: -40 to +85 °C

weight: 150 g

switching hysteresis¹⁾: 5 mmswitching frequency²⁾: 12 Hzresponse time²⁾: 64 ms

time delay before availability: <300 ms

mic+35/DD/TC

switching output: 2 x pnp, U_B - 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+35/EE/TC

switching output: 2 x npn, -U_B + 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+130...

±0.15 %
±1 % (Temperature drift internal compensated, may be deactivated³⁾, 0.17%/K without compensation)operating voltage U_B: 9 to 30 V DC, short-circuit-proof, Class 2

voltage ripple: ±10 %

no-load supply current: ≤ 80 mA

housing: Brass sleeve, nickel-plated, plastic parts: PBT, TPU; Ultrasonic transducer: polyurethane foam, epoxy resin with glass content

class of protection to EN 60529: IP 67

norm conformity: EN 60947-5-2

type of connection: 5-pin initiator plug, PBT

controls: 2 push-buttons (TouchControl)

indicators: 3-digit LED display, 2 three-colour LEDs with TouchControl and LinkControl

programmable: programmable

operating temperature: -25 to +70 °C

storage temperature: -40 to +85 °C

weight: 150 g

switching hysteresis¹⁾: 20 mmswitching frequency²⁾: 8 Hzresponse time²⁾: 92 ms

time delay before availability: <300 ms

mic+130/DD/TC

switching output: 2 x pnp, U_B - 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+130/EE/TC

switching output: 2 x npn, -U_B + 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+340...

±0.15 %
±1 % (Temperature drift internal compensated, may be deactivated³⁾, 0.17%/K without compensation)operating voltage U_B: 9 to 30 V DC, short-circuit-proof, Class 2

voltage ripple: ±10 %

no-load supply current: ≤ 80 mA

housing: Brass sleeve, nickel-plated, plastic parts: PBT, TPU; Ultrasonic transducer: polyurethane foam, epoxy resin with glass content

class of protection to EN 60529: IP 67

norm conformity: EN 60947-5-2

type of connection: 5-pin initiator plug, PBT

controls: 2 push-buttons (TouchControl)

indicators: 3-digit LED display, 2 three-colour LEDs with TouchControl and LinkControl

programmable: programmable

operating temperature: -25 to +70 °C

storage temperature: -40 to +85 °C

weight: 210 g

switching hysteresis¹⁾: 50 mmswitching frequency²⁾: 4 Hzresponse time²⁾: 172 ms

time delay before availability: <380 ms

mic+340/DD/TC

switching output: 2 x pnp, U_B - 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+340/EE/TC

switching output: 2 x npn, -U_B + 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+600...

±0.15 %
±1 % (Temperature drift internal compensated, may be deactivated³⁾, 0.17%/K without compensation)operating voltage U_B: 9 to 30 V DC, short-circuit-proof, Class 2

voltage ripple: ±10 %

no-load supply current: ≤ 80 mA

housing: Brass sleeve, nickel-plated, plastic parts: PBT, TPU; Ultrasonic transducer: polyurethane foam, epoxy resin with glass content

class of protection to EN 60529: IP 67

norm conformity: EN 60947-5-2

type of connection: 5-pin initiator plug, PBT

controls: 2 push-buttons (TouchControl)

indicators: 3-digit LED display, 2 three-colour LEDs with TouchControl and LinkControl

programmable: programmable

operating temperature: -25 to +70 °C

storage temperature: -40 to +85 °C

weight: 270 g

switching hysteresis¹⁾: 100 mmswitching frequency²⁾: 3 Hzresponse time²⁾: 240 ms

time delay before availability: <450 ms

mic+600/DD/TC

switching output: 2 x pnp, U_B - 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

mic+600/EE/TC

switching output: 2 x npn, -U_B + 2 V, I_{max} = 2 x 200 mA
switchable NOC/NCC, short-circuit-proof

Enclosure Type 1
 For use only in industrial
 machinery NFPA 79 applications.

The proximity switches shall be used with a
 Listed (CYV77) cable/connector assembly
 rated minimum 32 Vdc, minimum 290 mA,
 in the final installation.



Registration
 no. 75330-19
 Approved on
 June 25th, 2019



2014/30/EU
 IMV-DO-041943-761463