



Product description

- The lcs-sensor with two switched outputs measures the distance to an object within the detection zone contactless. Depending on the adjusted detect distance the switched outputs are set.
- The output functions are changeable from NOC to NCC.
- Light emitting diodes (three-colour LEDs) indicate the switching status.
- The sensors can be trained using Teach-in processes.
- Using the LinkControl adapter (optional accessory) all sensor parameter settings may be made by a Windows-Software.

sensor that can be applied with normal reflectors with sufficient function reserve. When using good reflectors, such as a calm water surface, the sensor can also be used up to its **maximum range**. Objects that strongly absorb (e.g. plastic foam) or diffusely reflect sound (e.g. pebble stones) can also reduce the defined operating range.

	3x	colour
1	+UB	brown
3	-UB	blue
4	D2	black
2	D1	white
5	D3/Com.	grey

Fig. 1: Pin assignment with view onto sensor plug and colour coding of the microsonic connection cable

Assembly instructions

- Assemble the sensor at the installation location.
- Plug in the connector cable to the M 12 connector.

Assembly distances

The assembly distances shown in Fig.2 for two or more sensors should not be fallen below in order to avoid mutual interference.




Fig. 2: Assembly distances

Start-up

lcs sensors are delivered factory made with the following settings:

- Switched outputs on NOC
- Detecting distances at operating range and half operating range
- Measurement range set to maximum range

Set the parameters of the sensor using the Teach-in procedure.

Operation

lcs-sensors work maintenance free. Small amounts of dirt on the surface do not influence function. Thick layers of dirt and caked-on dirt affect sensor function and therefore must be removed.

Note

- mic+ sensors have internal temperature compensation. Because the sensors heat up on their own, the temperature compensation reaches its optimum working point after approx. 30 minutes of operation.
- During normal mode operation, a yellow LED signals that the corresponding switched output has connected.
- During Teach-in mode, the hysteresis loops are set back to factory settings.
- If no signal is transmitted to the Com input for 20 s during parameter setting mode the made changes are stored and the sensor returns to normal mode operation.
- You can reset the factory settings at any time, see »Lock Teach-in & factory setting«.
- lcs-sensors optional can be programmed using the LinkControl adapter LCA-2, see «Optional setting of parameters using the LinkControl Adapter LCA-2».



2014/30/EU



MV-DO-074381-523848

Operating instructions

lcs-Ultrasonic Sensors with three switched outputs

lcs-25/DDD/QP

lcs-35/DDD/QP

lcs-130/DDD/QP

Important instructions for assembly and application

All employee and plant safety-relevant measures must be taken prior to assembly, start-up, or maintenance work (see operation manual for the entire plant and the operator instruction of the plant).

The sensors are not considered as safety equipment and may not be used to ensure human or machine safety!

The lcs-sensors indicate a **blind zone**, in which the distance cannot be measured. The **operating range** indicates the distance of the

① Download of sensor parameters in the LCA-1

888

F + T2

Press F + T2 at the LCA-2 simultaneously (ca. 1 sec)

8888888888

BUS88888888

Press R at the LCA-2 (ca. 1 sec)

8888

Parameters are transferred from the sensor to the LCA-2

888

Download of parameters completed

End

Current measurement value is displayed

895

③ Upload of sensor parameters back to the sensor

888

F + T1

Press F + T1 at the LCA-2 simultaneously (ca. 1 sec)

88888888

BUS88888888

Press R at the LCA-2 (ca. 1 sec)

8888

Parameters are transferred from the LCA-2 to the sensor

888

Upload of parameters completed

End

Current measurement value is displayed

895

Factory setting

Reset to factory setting


Turn supply voltage OFF

Turn supply voltage ON while »D3/Com« is connected to -UB


Keep »D3/Com« connected to -UB until both LEDs stop flashing (ca. 13 sec)

Normal mode operation


② Optional setting of parameters using the LinkControl Adapter LCA-2 (Offline programming)



②a Setting of additional functions in the LCA-2




Technical data




3 pnp switched outputs


D... Ics-25...



D... Ics-35...



D... Ics-130...



Blind zone: 0 to 30 mm

Operating range: 250 mm

Maximum range: 350 mm

Angle of beam spread: See detection zone

Transducer frequency: 320 kHz


Resolution, sampling rate: 0,18 mm

Reproducibility: $\pm 0,15\%$

Detection zones:

for different objects:
The dark grey areas are determined with a thin round bar (10 mm dia.) and indicate the typical operating range of a sensor. In order to obtain the light grey areas, a plate (100 x 100 mm) is introduced into the beam spread from the side.

In doing so, the optimum angle between plate and sensor is always employed. This therefore indicates the maximum detection zone of the sensor. It is not possible to evaluate ultrasonic reflections outside this area.



0 to 65 mm

350 mm

600 mm

See detection zone

400 kHz


0,18 mm

 $\pm 0,15\%$

Plate

Round

bar



0 to 200 mm

1.300 mm

2.000 mm

See detection zone

200 kHz


0,18 mm

 $\pm 0,15\%$

Plate

Round

bar



Accuracy:

Temperature drift internal compensated, $\leq 2\%$, may be deactivated¹⁾ (0,17%/K without compensation

9 V to 30 V DC, reverse polarity protection

Operating voltage U_B:Voltage ripple: $\pm 10\%$

No-load current consumption:

Housing: PBT

Class of protection to EN 60 529: IP 65

Norm conformity: EN 60947-5-2

Type of connection: No

Indicators: 3 three-colour LEDs

Programmable: Yes, with LCA-2 & LinkControl

Operating temperature: -25°C to +70°C

Storage temperature: -40°C to +85°C

Weight: 120 g

Switching hysteresis: 3 mm

Switching frequency¹⁾: 11 HzResponse time¹⁾: 50 ms

Time delay before availability: < 300 ms

Order no.: Ics-25/DDD/QP

Switched output: 3 * pnp, U_B-2 V, I_{max} = 200 mA
switchable NOC/NCC, short-circuit-proofTemperature drift internal compensated, $\leq 2\%$, may be deactivated¹⁾ (0,17%/K without compensation

9 V to 30 V DC, reverse polarity protection

 $\pm 10\%$

< 70 mA

PBT

Class of protection to EN 60 529: IP 65

Norm conformity: EN 60947-5-2

Type of connection: No

Indicators: 3 three-colour LEDs

Programmable: Yes, with LCA-2 & LinkControl

Operating temperature: -25°C to +70°C

Storage temperature: -40°C to +85°C

Weight: 120 g

Switching hysteresis: 5 mm

Switching frequency¹⁾: 8 HzResponse time¹⁾: 70 ms

Time delay before availability: 110 ms

Order no.: Ics-35/DDD/QP

Switched output: 3 * pnp, U_B-2 V, I_{max} = 200 mA
switchable NOC/NCC, short-circuit-proof

Ics-130/DDD/QP

Switched output: 3 * pnp, U_B-2 V, I_{max} = 200 mA
switchable NOC/NCC, short-circuit-proof

1) Can be programmed with LinkControl