Digital Input

LB1001A

- 2 channels
- Dry contact or NAMUR inputs
- Installation in Zone 2 or safe area
- Galvanic isolation between channels and the bus
- Positive or negative logic selectable
- Simulation mode for service operations (forcing)
- Line fault detection (LFD)
- Permanently self-monitoring
- Module can be exchanged under voltage







Function

The device accepts up to 2 digital input signals of NAMUR sensors or mechanical contacts from the field. Open or short circuit line fault alarms are detected. The inputs are galvanically isolated from each other, from the bus and the power supply (EN 60079-11).

Connection





Zone 2

Technical Data

Slots		
Occupied slots		1
Supply		
Connection		backplane bus
Rated voltage	Ur	12 V DC , only in connection with the power supplies LB9***
Power dissipation		0.65 W
Power consumption		0.65 W
Electrical specifications		
Galvanic isolation		Galvanic isolation between channels
Internal bus		
Connection		backplane bus
Interface		manufacturer-specific bus to standard com unit
Digital input		

Technical Data Number of channels Sensor interface Connection NAMUR sensor Connection [2] volt-free contact Connection channel I: 1+, 2/3-; channel II: 4+, 5/6-Rated values acc. to EN 60947-5-6 (NAMUR) Switching point/switching hysteresis $1.2 \dots 2.1 \text{ mA} / \pm 0.2 \text{ mA}$ 8.2 V Voltage Internal resistor R_i 1 kΩ Line fault detection can be switched on/off for each channel via configuration tool Connection mechanical switch with additional resistors (see connection diagram) proximity switches without additional wiring < 360 Ω Short-circuit < 0.35 mA Open-circuit Minimum pulse duration 20 ms Indicators/settings LED indication Power LED (P) green: supply Status LED (1, 3) red: line fault (per channel) Status LED (2, 4) yellow: signal (per channel) Coding optional mechanical coding via front socket **Directive conformity** Electromagnetic compatibility Directive 2014/30/EU EN 61326-1:2013 Conformity Electromagnetic compatibility NF 21 Degree of protection IEC 60529 Environmental test EN 60068-2-14 Shock resistance EN 60068-2-27 EN 60068-2-6 Vibration resistance EN 60068-2-42 Damaging gas Relative humidity EN 60068-2-78 **Ambient conditions** Ambient temperature -40 ... 60 °C (-40 ... 140 °F) , 70 °C (non-Ex) Storage temperature -40 ... 85 °C (-40 ... 185 °F) Relative humidity 95 % non-condensing Altitude max. 2000 m Shock resistance shock type I, shock duration 11 ms, shock amplitude 15 g, number of shocks 18 Vibration resistance frequency range 10 ... 150 Hz; transition frequency: 57.56 Hz, amplitude/acceleration ± 0.075 mm/1 g; 10 cycles frequency range 5 ... 100 Hz; transition frequency: 13.2 Hz amplitude/acceleration ± 1 mm/0.7 g; 90 minutes at each resonance designed for operation in environmental conditions acc. to ISA-S71.04-1985, severity level ${\sf G3}$ Damaging gas Mechanical specifications Degree of protection IP20 when mounted on backplane removable front connector with screw flange (accessory) wiring connection via spring terminals (0.14 ... 1.5 mm²) or screw terminals (0.08 ... 1.5 mm²) Connection Mass **Dimensions** 16 x 100 x 102 mm (0.63 x 3.9 x 4 inch) Data for application in connection with hazardous areas Certificate PF 08 CERT 1234 X Marking Galvanic isolation Input/power supply, internal bus safe electrical isolation acc. to EN 60079-11, voltage peak value 375 V Directive conformity

Technical Data	
Directive 2014/34/EU	EN IEC 60079-0:2018+AC:2020 EN 60079-11:2012 EN 60079-15:2010
International approvals	
IECEx approval	
IECEx certificate	IECEx BVS 09.0037X
IECEx marking	Ex nA [ic] IIC T4 Gc
General information	
System information	The module has to be mounted in appropriate backplanes (LB9***) in Zone 2 or outside hazardous areas. Here, observe the corresponding declaration of conformity. For use in hazardous areas (e. g. Zone 2 or Zone 22) the module must be installed in an appropriate enclosure.
Supplementary information	EC-Type Examination Certificate, Statement of Conformity, Declaration of Conformity, Attestation of Conformity and instructions have to be observed where applicable. For information see www.pepperl-fuchs.com.

Assembly

