

Backlight


ZVZF302

Part Number



- Continuous mode or flash mode synchronized with the camera
- Diffuse light for transmitted light and incident light applications
- Rugged housing (IP67) with minimal thickness and narrow framing

wenglor backlights are ideally suited for vision applications in which large areas need to be illuminated. They can be operated in the continuous mode, or synchronized to the digital camera in the flash mode. Thanks to their diffuse light, the backlights are ideal for applications with transmitted light or incident light. Above all in systems where space is limited, users profit from the rugged housing (IP67) with minimal thickness and narrow framing, and at the same time from the large illuminated surface area.



Technical Data

Optical Data

Light Source	White Light
Color temperature	5000 K
Service Life (T = +25 °C)	100000 h
Luminance (Continuous Mode)	7400 cd/m ²
Luminance (Flash Mode)	31000 cd/m ²

Electrical Data

Supply Voltage	18...30 V DC
Current Consumption Flash Mode (U _b = 24 V)	< 4800 mA
Current Consumption Continuous Mode (U _b = 24 V)	< 850 mA
Flash Duration	17...30000 µs
Duty Cycle	< 0,2
Temperature Range	-30...50 °C
Storage temperature	-30...60 °C
Short Circuit Protection	yes
Reverse Polarity Protection	yes
Overload Protection	yes
Protection Class	III

Mechanical Data

Luminous field	180 × 180 mm
Housing Material	Aluminum, anodised
Optic Cover	PMMA
Degree of Protection	IP67
Connection	M12 × 1; 4/5-pin


Safety-relevant Data

MTTFd (EN ISO 13849-1)	89,81 a
------------------------	---------

Connection Diagram No.	181
Connection Table No.	60
Suitable Connection Equipment No.	37


Complementary Products

Connection Cable ZC4G001



All dimensions in mm (1 mm = 0.03937 Inch)

181



Legend

+	Supply Voltage +	PT	Platinum measuring resistor
-	Supply Voltage 0 V	nc	not connected
~	Supply Voltage (AC Voltage)	U	Test Input
A	Switching Output (NO)	U	Test Input inverted
Ā	Switching Output (NC)	W	Trigger Input
V	Contamination/Error Output (NO)	W-	Ground for the Trigger Input
Ṽ	Contamination/Error Output (NC)	O	Analog Output
E	Input (analog or digital)	O-	Ground for the Analog Output
T	Teach Input	BZ	Block Discharge
Z	Time Delay (activation)	AWV	Valve Output
S	Shielding	a	Valve Control Output +
RxD	Interface Receive Path	b	Valve Control Output 0 V
TxD	Interface Send Path	SY	Synchronization
RDY	Ready	SY-	Ground for the Synchronization
GND	Ground	E+	Receiver-Line
CL	Clock	S+	Emitter-Line
E/A	Output/Input programmable	±	Grounding
IO-Link	IO-Link	SnR	Switching Distance Reduction
PoE	Power over Ethernet	Rx+/-	Ethernet Receive Path
IN	Safety Input	Tx+/-	Ethernet Send Path
OSSD	Safety Output	Bus	Interfaces-Bus A(+)/B(-)
Signal	Signal Output	La	Emitted Light disengageable
BI-D+/-	Ethernet Gigabit bidirect. data line (A-D)	Mag	Magnet activation
EN0.05422	Encoder 0-pulse 0-0 (TTL)	RES	Input confirmation
		EDM	Contact Monitoring

EN0.05422	Encoder A/Ā (TTL)
EN0.05422	Encoder B/B̄ (TTL)
ENa	Encoder A
ENb	Encoder B
AMIN	Digital output MIN
AMAX	Digital output MAX
AOK	Digital output OK
SY in	Synchronization In
SY OUT	Synchronization OUT
OLt	Brightness output
M	Maintenance
rsv	reserved
Wire Colors according to IEC 60757	
BK	Black
BN	Brown
RD	Red
OG	Orange
YE	Yellow
GN	Green
BU	Blue
VT	Violet
GY	Grey
WH	White
PK	Pink
GNYE	Green/Yellow

