

XUY712NF1P2  
Photoelectric sensors XU, Roller Sensor 712  
mm N1, P88.9 IP50 2 Hexa. Cable 2 m,Wires



Main

|                          |                                        |
|--------------------------|----------------------------------------|
| Range of product         | Telemecanique Photoelectric sensors XU |
| Series name              | Application                            |
| Electronic sensor type   | Photo-electric sensor                  |
| Sensor name              | XUY                                    |
| Type of output signal    | Discrete                               |
| Supply circuit type      | DC                                     |
| Wiring technique         | 4-wire                                 |
| Discrete output function | 1 NO or 1 NC programmable              |
| Electrical connection    | Cable                                  |

Complementary

|                           |                                                               |
|---------------------------|---------------------------------------------------------------|
| [Us] rated supply voltage | 12...24 V DC with reverse polarity protection                 |
| Maximum voltage drop      | <2 V at 100 mA (closed state)<br><1 V at 10 mA (closed state) |

Environment

|                                       |                 |
|---------------------------------------|-----------------|
| Product certifications                | cULus[RETURN]CE |
| Ambient air temperature for operation | 0...50 °C       |
| Ambient air temperature for storage   | -20...80 °C     |

Packing Units

|                              |        |
|------------------------------|--------|
| Unit Type of Package 1       | PCE    |
| Number of Units in Package 1 | 1      |
| Package 1 Height             | 9 cm   |
| Package 1 Width              | 9 cm   |
| Package 1 Length             | 100 cm |
| Package 1 Weight             | 800 g  |

The information provided in this documentation contains general descriptions and/or technical characteristics of the products of the company. This information is not intended to be used for determining suitability or reliability of these products for specific user applications. It is the duty of any such user or integrator to perform the appropriate and complete risk analysis, evaluation and testing of the products with respect to the relevant specific application or use thereof. Neither TWSS Holding nor any of its affiliates or subsidiaries shall be responsible or liable for misuse of the information contained herein.