

Telemecanique Emergency stop rope pull switches XY2C, mounting kit, Ø 3.2 mm, L 30.5 m



Main

|                                    |  |
|------------------------------------|--|
| Range of product                   | Telemecanique Emergency stop rope pull switches XY2C |
| Accessory / separate part type     | Mounting kit   |
| Accessory / separate part category | Mounting and fixing accessories                      |

Complementary

|                                       |  |
|---------------------------------------|--|
| Product compatibility                 | XY2CJ  |
| Accessory / separate part destination | Emergency stop rope pull switch  |
| Kit composition                       | 1 x cable grip XY2CZ523<br>1 x end spring XY2CZ703<br>1 x galvanised cable<br>1 x cable support XY2CZ601<br>1 x tensioner XY2CZ210<br>1 x cable end protector XY2CZ701 |
| Cable outer diameter                  | 3.2 mm   |
| Cable length                          | 30.5 m   |
| Net weight                            | 2.045 kg   |

Packing Units

|                              |           |
|------------------------------|-----------|
| Unit Type of Package 1       | PCE       |
| Number of Units in Package 1 | 1         |
| Package 1 Height             | 4.500 cm  |
| Package 1 Width              | 19.500 cm |
| Package 1 Length             | 19.500 cm |
| Package 1 Weight             | 1.418 kg  |
| Unit Type of Package 2       | S02       |
| Number of Units in Package 2 | 5         |
| Package 2 Height             | 15 cm     |
| Package 2 Width              | 30 cm     |
| Package 2 Length             | 40 cm     |
| Package 2 Weight             | 7.395 kg  |

Offer Sustainability

|  |   |
|--|---|
| California proposition 65                  | WARNING: This product can expose you to chemicals including: Diisononyl phthalate (DINP), which is known to the State of California to cause cancer, and Di-isodecyl phthalate (DIDP), which is known to the State of California to cause birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a> |
| For all Reach Rohs enquiries contact us at | <a href="mailto:sustainability@tesensors.com">sustainability@tesensors.com</a>  |